

LABELVIEW 8.60 Installation Scenarios

Click on your installation scenario below to view the associated instruction set.

[Scenario 1: Single User, Full Install, Software Key Protection, Demo already installed](#)

[Scenario 2: Single User, Full Install, Software Key Protection, Demo not installed](#)

[Scenario 3: Single User, Upgrade, Migrating from Hardware Key Protection to Software Key Protection](#)

[Scenario 4: Single User, Upgrade, Continuing to Use Hardware Key Protection](#)

[Scenario 5: Network, Full Install](#)

[Scenario 6: Network, Upgrade, Migrating from Hardware Key Protection to Software Key Protection](#)

[Scenario 7: Network, Upgrade, Continuing to Use Hardware Key Protection](#)

[Scenario 8: Going from a Single User Version with Hardware Key Protection to a Network Version with Software Key Protection](#)

[Scenario 9: Network, Citrix/Terminal Service Install](#)

[Scenario 10: Add User Licenses or Product Add-Ons, Software Key Protection](#)

[Scenario 11: Add User Licenses or Product Add-Ons, Hardware Key Protection](#)

[Scenario 12: Edition Upgrade, Software Key Protection](#)

[Scenario 13: Edition Upgrade, Hardware Key Protection](#)

Scenario 1: Single User, Full Install, Software Key Protection, Demo already installed

If you have already downloaded and installed the **current** LABELVIEW Demo, there is no need to install again from the CD. You simply need to activate the product to convert it from a trial version to a full product.

A) Activate the software:

1. Start LABELVIEW. A welcome screen appears displaying options to activate the software immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

[Back to Index](#)

Scenario 2: Single User, Full Install, Software Key Protection, Demo not installed

A-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.

A-2) Install from the CD:

1. Insert the CD. The CD's opening screen will appear.

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.

2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

4. Proceed with the installation process by following the on-screen instructions provided in the wizard.

B) Activate the software:

1. Start LABELVIEW. A welcome screen appears displaying options to activate the software immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

[Back to Index](#)

Scenario 3: Single User, Upgrade, Migrating from Hardware Key Protection to Software Key Protection

A-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.

A-2) Install from the CD:

1. Insert the CD. The CD's opening screen will appear.
If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.
4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.

B) Activate the software:

1. Start LABELVIEW. A welcome screen appears displaying options to activate the software immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

C) Return your key to TEKLYNX:

After you have activated your software, please mail your software key to:

TEKLYNX International
P.O. Box 1786
Milwaukee, WI 53201-1786

[Back to Index](#)

Scenario 4: Single User, Upgrade, Continuing to Use Hardware Key Protection

If you have LABELVIEW version 6.0 or above (with Hardware Key protection) and you are upgrading to the latest version and keeping Hardware Key protection, this is known as a Hardware Key to Hardware Key upgrade.

A-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.

2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.

A-2) Install LABELVIEW from the CD:

1. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
2. Select the desired language for the software interface screens, and then click **OK**.
3. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

Note: If the earlier version is currently installed on the computer, you should install the new version over the earlier version. This way, any configuration settings you previously set up in the earlier version will be saved.

4. Proceed with the installation process by following the on-screen instructions provided in the wizard.

B) Run the Key Upgrade Utility:

1. To access the Key Upgrade utility, go to **Start > Programs > Teklynx > Upgrade Manager > Key - Upgrade**.

The Key Upgrade wizard will appear.

2. Proceed with the Key Upgrade process by following the on-screen instructions provided in the wizard.

Note: If you get a message that the key could not be found, check that your key is correctly connected to the parallel or USB port. If your connection is fine, check to make sure your HASP drivers are upgraded before upgrading your key. A HASP upgrade wizard is available at www.teklynx.com/HASP.

[Back to Index](#)

Scenario 5: Network, Full Install

To use the Network (multi-user) version of LABELVIEW, you must install the Network Management Utilities (License Manager and/or License Service) on the server or on a station that will act as a server, and then install the LABELVIEW software on each client workstation. You can also run the Network Management Utilities from the TEKLYNX web site if you do not have a product CD.

A) Install the Network Management Utilities:

1. Insert the CD on the computer chosen to act as the license server. The CD's opening screen will appear.

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **Network Manager** and then click the **Install** button.

The install program begins preparations for the Label Design Network Utilities setup process (this may take a moment).
3. On the **Protection type** screen, select the appropriate protection type based on the product you purchased (either a Software Key or Hardware Key version), and then click **Next**.
4. Proceed with the installation of the Network Management Utilities by following the on-screen instructions provided in the wizard.

B) Share the Network License Folder:

1. On the license server machine, in Windows Explorer, navigate to select the network license folder.
 - For **Windows 2000, Windows XP, or Windows Server 2003**, this folder is located at C:\Documents and Settings\All Users\Application Data\TKI\LicenseManager\TkDongle. (Note: The Application Data folder is a "hidden" folder. Depending on the operating system, you may need to be logged in as the Administrator in order to view hidden files.)
 - For **Windows Vista, Windows 7, Windows Server 2008, and Windows Server 2008 R2**, this folder is located at C:\Program Data\TKI\TkDongle.
2. Right-click on the TkDongle folder and click **Share**.
3. Create a new share and name it **TkDongle** (case sensitive).
4. Give the required users full Read/Write/Modify access to the shared folder.

C) Activate License Manager:

1. Start License Manager. A welcome screen appears displaying options to activate immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

D) Start License Manager/License Service:

- *If you installed License Manager*, before installing LABELVIEW on all the workstations, you must start License Manager by going to **Start > All Programs > Teklynx > Network and User Utilities > Network Toolbar**.
- *If you installed License Service*, it will launch automatically when the system is powered on and will run as a background task as long as the workstation is on. (Note: You can run License Service Control to monitor the status of the License Service.)

E) Install the LABELVIEW software on all client workstations

E-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.

E-2) Install from CD:

1. Insert the CD. The CD's opening screen will appear.
If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.

3. Select the desired language for the software interface screens, and then click **OK**.
4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.
6. Start LABELVIEW.
7. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
8. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.
9. Close and restart LABELVIEW to complete the network installation.

[Back to Index](#)

Scenario 6: Network, Upgrade, Migrating from Hardware Key Protection to Software Key Protection

A) Remove the Existing Network Management Utilities (License Manager and/or License Service)

1. If License Service is running, from **Control Panel > Administrative Tools > Services**, stop the Slicense Service.
2. Still in Control Panel, use the **Add or Remove Programs** option (or **Programs and Features** option in Windows Vista or Server 2008) to uninstall the License Manager or Network Management Utilities.

B) Install the Network Management Utilities:

1. Insert the CD on the computer chosen to act as the license server. The CD's opening screen will appear. (You can also run the Network Management Utilities from the TEKLYNX web site if you do not have a product CD.)

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **Network Manager** and then click the **Install** button.

The install program begins preparations for the Label Design Network Utilities setup process (this may take a moment).

3. On the **Protection type** screen, select the appropriate protection type based on the product you purchased (either a Software Key or Hardware Key version), and then click **Next**.
4. Proceed with the installation of the Network Management Utilities by following the on-screen instructions provided in the wizard.

C) Share the Network License Folder:

1. On the license server machine, in Windows Explorer, navigate to select the network license folder.
 - For **Windows 2000, Windows XP, or Windows Server 2003**, this folder is located at C:\Documents and Settings\All Users\Application Data\TKI\LicenseManager\TkDongle. (Note: The Application Data folder is a "hidden" folder. Depending on the operating system, you may need to be logged in as the Administrator in order to view hidden files.)
 - For **Windows Vista, Windows 7, Windows Server 2008, and Windows Server 2008 R2**, this folder is located at C:\Program Data\TKI\TkDongle.
2. Right-click on the TkDongle folder and click **Share**.
3. Create a new share and name it **TkDongle** (case sensitive).
4. Give the required users full Read/Write/Modify access to the shared folder.

D) Activate License Manager:

1. Start License Manager. A welcome screen appears displaying options to activate immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

E) Start License Manager/License Service:

- ***If you installed License Manager***, before installing LABELVIEW on all the workstations, you must start License Manager by going to **Start > All Programs > Teklynx > Network and User Utilities > Network Toolbar**.
- ***If you installed License Service***, it will launch automatically when the system is powered on and will run as a background task as long as the workstation is on. (Note: You can run License Service Control to monitor the status of the License Service.)

F) Install the LABELVIEW software on all client workstations:

F-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.
7. Start LABELVIEW.
8. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
9. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.
10. Close and restart LABELVIEW to complete the network installation.

F-2) Install from CD:

1. Insert the CD. The CD's opening screen will appear.
If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.
4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.
6. Start LABELVIEW.
7. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
8. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.

9. Close and restart LABELVIEW to complete the network installation.

G) Return your key to TEKLYNX:

After you have activated your software, please mail your software key to:

TEKLYNX International
P.O. Box 1786
Milwaukee, WI 53201-1786

[Back to Index](#)

Scenario 7: Network, Upgrade, Continuing to Use Hardware Key Protection

If you have LABELVIEW version 6.0 or above (with Hardware Key protection) and you are upgrading to the latest version and keeping Hardware Key protection, this is known as a Hardware Key to Hardware Key upgrade.

A) Remove the Existing Network Management Utilities (License Manager and/or License Service)

1. If License Service is running, from **Control Panel > Administrative Tools > Services**, stop the Slicense Service.
2. Still in Control Panel, use the **Add or Remove Programs** option (or **Programs and Features** option in Windows Vista or Server 2008) to uninstall the License Manager or Network Management Utilities.

B) Install the Network Management Utilities:

1. Insert the CD on the computer chosen to act as the license server. The CD's opening screen will appear.

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **Network Manager** and then click the **Install** button.

The install program begins preparations for the Label Design Network Utilities setup process (this may take a moment).
3. On the **Protection type** screen, select the appropriate protection type based on the product you purchased (either a Software Key or Hardware Key version), and then click **Next**.
4. Proceed with the installation of the Network Management Utilities by following the on-screen instructions provided in the wizard.

C) Run the Key Upgrade Utility:

1. To access the Key Upgrade utility, go to **Start > Programs > Teklynx > Upgrade Manager > Key - Upgrade**.

The Key Upgrade wizard will appear.

2. Proceed with the Key Upgrade process by following the on-screen instructions provided in the wizard.

Note: If you get a message that the key could not be found, check that your key is correctly connected to the parallel or USB port. If your connection is fine, check to make sure your HASP drivers are upgraded before upgrading your key. A HASP upgrade wizard is available at www.teklynx.com/HASP.

D) Share the Network License Folder:

1. On the license server machine, in Windows Explorer, navigate to select the network license folder.
 - For **Windows 2000, Windows XP, or Windows Server 2003**, this folder is located at C:\Documents and Settings\All Users\Application Data\TKI\LicenseManager\TkDongle. (Note: The Application Data folder is a "hidden" folder. Depending on the operating system, you may need to be logged in as the Administrator in order to view hidden files.)
 - For **Windows Vista, Windows 7, Windows Server 2008, and Windows Server 2008 R2**, this folder is located at C:\Program Data\TKI\TkDongle.
2. Right-click on the TkDongle folder and click **Share**.
3. Create a new share and name it **TkDongle** (case sensitive).
4. Give the required users full Read/Write/Modify access to the shared folder.

E) Start License Manager/License Service:

- ***If you installed License Manager***, before installing LABELVIEW on all the workstations, you must start License Manager by going to **Start > All Programs > Teklynx > Network Manager**.
- ***If you installed License Service***, it will launch automatically when the system is powered on and will run as a background task as long as the workstation is on. (Note: You can run License Service Control to monitor the status of the License Service.)

F) Install the LABELVIEW software on all client workstations:

1. Insert the CD. The CD's opening screen will appear.

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.

2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.
4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.
6. Start LABELVIEW.
7. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
8. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.
9. Close and restart LABELVIEW to complete the network installation.

[Back to Index](#)

Scenario 8: Going from a Single User Version with Hardware Key Protection to a Network Version with Software Key Protection

A) Install the Network Management Utilities:

1. Insert the CD on the computer chosen to act as the license server. The CD's opening screen will appear. (You can also run the Network Management Utilities from the TEKLYNX web site if you do not have a product CD.)

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **Network Manager** and then click the **Install** button.

The install program begins preparations for the Label Design Network Utilities setup process (this may take a moment).
3. On the **Protection type** screen, select the appropriate protection type based on the product you purchased (either a Software Key or Hardware Key version), and then click **Next**.
4. Proceed with the installation of the Network Management Utilities by following the on-screen instructions provided in the wizard.

B) Share the Network License Folder:

1. On the license server machine, in Windows Explorer, navigate to select the network license folder.
 - For **Windows 2000, Windows XP, or Windows Server 2003**, this folder is located at C:\Documents and Settings\All Users\Application Data\TKI\LicenseManager\TkDongle. (Note: The Application Data folder is a "hidden" folder. Depending on the operating system, you may need to be logged in as the Administrator in order to view hidden files.)
 - For **Windows Vista, Windows 7, Windows Server 2008, and Windows Server 2008 R2**, this folder is located at C:\Program Data\TKI\TkDongle.
2. Right-click on the TkDongle folder and click **Share**.
3. Create a new share and name it **TkDongle** (case sensitive).
4. Give the required users full Read/Write/Modify access to the shared folder.

C) Activate License Manager:

1. Start License Manager. A welcome screen appears displaying options to activate immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

D) Start License Manager/License Service:

- ***If you installed License Manager***, before installing LABELVIEW on all the workstations, you must start License Manager by going to **Start > All Programs > Teklynx > Network and User Utilities > Network Toolbar**.
- ***If you installed License Service***, it will launch automatically when the system is powered on and will run as a background task as long as the workstation is on. (Note: You can run License Service Control to monitor the status of the License Service.)

E) Install the LABELVIEW software on all client workstations:

E-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.

4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.
The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
6. Proceed with the installation process by following the on-screen instructions provided in the wizard.
7. Start LABELVIEW.
8. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
9. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., *ServerName*) that Network Manager was installed on.
10. Close and restart LABELVIEW to complete the network installation.

E-2) Install from CD:

1. Insert the CD. The CD's opening screen will appear.
If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.
4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.
6. Start LABELVIEW.
7. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
8. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., *ServerName*) that Network Manager was installed on.
9. Close and restart LABELVIEW to complete the network installation.

[Back to Index](#)

Scenario 9: Network, Citrix/Terminal Service Install

A) Install the Network Management Utilities:

1. Insert the CD on the computer chosen to act as the license server. The CD's opening screen will appear. (You can also run the Network Management Utilities from the TEKLYNX web site if you do not have a product CD.)

If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **Network Manager** and then click the **Install** button.

The install program begins preparations for the Label Design Network Utilities setup process (this may take a moment).
3. On the **Protection type** screen, select the appropriate protection type based on the product you purchased (either a Software Key or Hardware Key version), and then click **Next**.
4. Proceed with the installation of the Network Management Utilities by following the on-screen instructions provided in the wizard.

B) Share the Network License Folder:

1. On the license server machine, in Windows Explorer, navigate to select the network license folder.
 - For **Windows 2000, Windows XP, or Windows Server 2003**, this folder is located at C:\Documents and Settings\All Users\Application Data\TKI\LicenseManager\TkDongle. (Note: The Application Data folder is a "hidden" folder. Depending on the operating system, you may need to be logged in as the Administrator in order to view hidden files.)
 - For **Windows Vista, Windows 7, Windows Server 2008, and Windows Server 2008 R2**, this folder is located at C:\Program Data\TKI\TkDongle.
2. Right-click on the TkDongle folder and click **Share**.
3. Create a new share and name it **TkDongle** (case sensitive).
4. Give the required users full Read/Write/Modify access to the shared folder.

C) Activate License Manager:

1. Start License Manager. A welcome screen appears displaying options to activate immediately or to try it for an evaluation period.
2. Click **Activate**.
3. Proceed with the activation process by following the on-screen instructions provided in the wizard.

D) Start License Manager/License Service:

- ***If you installed License Manager***, before installing LABELVIEW on all the workstations, you must start License Manager by going to **Start > All Programs > Teklynx > Network and User Utilities > Network Toolbar**.
- ***If you installed License Service***, it will launch automatically when the system is powered on and will run as a background task as long as the workstation is on. (Note: You can run License Service Control to monitor the status of the License Service.)

E) Perform Client Installs on the Server:

E-1) Install from electronic delivery:

1. Open the e-mail message from TEKLYNX containing your software installation information. Click the hyperlink to download the software.
2. On the TEKLYNX Download Center page, click the **Download LABELVIEW** link. The File Download – Security Warning window opens.
3. Click **Save** to download the executable file to your computer. Be sure to note the location where the file is saved.
4. Double-click the executable file. If a security warning appears, click **Run**.
5. The Choose Setup Language window opens. Select the desired language for the software interface screens, and then click **OK**.

The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.

6. Proceed with the installation process by following the on-screen instructions provided in the wizard.
7. Start LABELVIEW.
8. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
9. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.
10. Close and restart LABELVIEW to complete the network installation.

E-2) Install from CD:

1. Insert the CD on the server. The CD's opening screen will appear.
If the CD does not automatically open, go to Windows Explorer and locate the CD-ROM drive letter and click on it to view its contents. Double-click on the **CDSetup.exe** file located on the CD.
2. On the opening screen of the CD, click on **LABELVIEW**, and then click the **Install** button.
3. Select the desired language for the software interface screens, and then click **OK**.

4. The **Preparing to Install** screen will appear, followed by the welcome screen for the installation wizard.
5. Proceed with the installation process by following the on-screen instructions provided in the wizard.
6. Start LABELVIEW.
7. On the **Options** menu, click **Configuration**, and then click the **Network** tab.
8. Click the **Network Key** check box, and use the Browse button or **Auto Find...** button to locate the server (e.g., \\ServerName) that Network Manager was installed on.
9. Close and restart LABELVIEW to complete the network installation.

F) Perform all needed configurations and printer installations

1. Start the LABELVIEW software again. If the license server install was configured properly, LABELVIEW will open without error, and License Manager or License Service should reflect one user accessing the program.
2. Set up all LABELVIEW configuration options as follows:
 - On the **Options** menu, click **Configuration**. Use the tabs on the **Configuration** dialog box to set up all LABELVIEW configuration settings that you want to be available for all users (i.e., network licensing, printing options, display language, etc.).
 - On the **Options** menu, click **Directories**. Use the **Directories** dialog box settings to specify the directory path for each data source option you want to be available for all users.
 - Configure any other **Options** menu settings (serial files, accumulator files, label inventory, etc.) that you want to be available for all users.
3. After all configuration options are set, close LABELVIEW to update the label.ini configuration file with the new settings.

Note: With Terminal Server/Citrix Server installations, each terminal will have its own unique LABELVIEW configuration file. For this reason, you **MUST** set all configuration options before setting up each remote terminal. Note that if system security is desired, this will also need to be set up **BEFORE** setting up the remote terminals.
4. Set up all remote terminals.
5. Now you can log onto the server or any remote terminal and the configuration file will be copied to each user as the user logs into the workstation or server and executes the LV.exe program file.

[Back to Index](#)

Scenario 10: Add User Licenses or Product Add-Ons, Software Key Protection

The process below allows you to upgrade an existing LABELVIEW product (Software Key protection) with additional user licenses or product add-ons.

A) Upgrade your software:

A-1) Upgrade online:

1. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

2. Click **Upgrade Software License**.
3. The user information associated with the license is displayed if you have an active Internet connection. If an open connection is not found, click **Upgrade Online** and enter proxy server information. Click **Next**.
4. In the **Serial Number** field, enter the upgrade license ID.
5. In the **Password** field, enter the upgrade password and click **Next**.
6. A success message is displayed. Click **Finish**.

A-2) Upgrade from another PC:

1. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

2. Click **Upgrade Software License**.
3. Click **Upgrade From Another Computer**.
4. On the Upgrade from Another Computer window, enter the upgrade information. Click **Next** and select the USB key.
5. When the Summary window appears, disconnect the USB key and connect the key to a computer that is connected to the Internet.
6. Launch the USB key from Windows Explorer.
7. Double-click **USBWizard.exe**.
8. On the home screen, select a license to activate and click **Next**.
9. Enter your SMA information if prompted.
10. When the Summary window appears, click **Finish**, then disconnect the USB key and connect to the original computer to activate.
11. On the original computer, launch the USB key from Windows Explorer.

12. Double-click USBWizard.exe.
13. The USB Activation screen displays the license that can be used on this computer. Click **Next**.
14. A success message is displayed. Click **Finish**.

A-3) Upgrade via e-mail:

1. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

2. Click **Upgrade Software License**.
3. On the second Upgrade Mode screen, click **Upgrade offline**.
4. On the second Activation Mode screen, click **Upgrade by e-mail**.
5. On the License Information screen, enter your serial number and password.
6. An e-mail is automatically sent to activations@teklynx.com. You will receive a reply message that contains your validation code.
7. Once you have received the reply message from TEKLYNX, access the Upgrade Manager and enter the validation code and installation code that were sent in the reply e-mail.
8. A success message is displayed. Click **Finish**.

[Back to Index](#)

Scenario 11: Add User Licenses or Product Add-Ons, Hardware Key Protection

The process below allows you to upgrade an existing LABELVIEW product (Hardware Key protection) with additional user licenses or product add-ons.

A) Run the Key Upgrade Utility:

1. To access the Key Upgrade utility, go to **Start > Programs > Teklynx > Upgrade Manager > Key - Upgrade**.

The Key Upgrade wizard will appear.

2. Proceed with the Key Upgrade process by following the on-screen instructions provided in the wizard.

Note: If you get a message that the key could not be found, check that your key is correctly connected to the parallel or USB port. If your connection is

fine, check to make sure your HASP drivers are upgraded before upgrading your key. A HASP upgrade wizard is available at www.teklynx.com/HASP.

[Back to Index](#)

Scenario 12: Edition Upgrade, Software Key Protection

The process below allows you to perform an Edition Upgrade (LV Basic to LV Pro, LV Basic to LV Gold, or LV Pro to LV Gold) to an existing LABELVIEW product (Software Key protection).

A) Upgrade your software:

A-1) Upgrade online:

7. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

8. Click **Upgrade Software License**.
9. The user information associated with the license is displayed if you have an active Internet connection. If an open connection is not found, click **Upgrade Online** and enter proxy server information. Click **Next**.
10. In the **Serial Number** field, enter the upgrade license ID.
11. In the **Password** field, enter the upgrade password and click **Next**.
12. A success message is displayed. Click **Finish**.

A-2) Upgrade from another PC:

1. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

2. Click **Upgrade Software License**.
3. Click **Upgrade From Another Computer**.
4. On the Upgrade from Another Computer window, enter the upgrade information. Click **Next** and select the USB key.
5. When the Summary window appears, disconnect the USB key and connect the key to a computer that is connected to the Internet.
6. Launch the USB key from Windows Explorer.

7. Double-click **USBWizard.exe**.
8. On the home screen, select a license to activate and click **Next**.
9. Enter your SMA information if prompted.
10. When the Summary window appears, click **Finish**, then disconnect the USB key and connect to the original computer to activate.
11. On the original computer, launch the USB key from Windows Explorer.
12. Double-click USBWizard.exe.
13. The USB Activation screen displays the license that can be used on this computer. Click **Next**.
14. A success message is displayed. Click **Finish**.

A-3) Upgrade via e-mail:

1. Launch the Upgrade Manager from **Start > All Programs > TEKLYNX > LABELVIEW > Upgrade Manager**.

For network versions, go to **Start > All Programs > TEKLYNX > Network and User Utilities > Network Toolbar**, then launch the License Upgrade for Network Versions application.

2. Click **Upgrade Software License**.
3. On the second Upgrade Mode screen, click **Upgrade offline**.
4. On the second Activation Mode screen, click **Upgrade by e-mail**.
5. On the License Information screen, enter your serial number and password.
6. An e-mail is automatically sent to activations@teklynx.com. You will receive a reply message that contains your validation code.
7. Once you have received the reply message from TEKLYNX, access the Upgrade Manager and enter the validation code and installation code that were sent in the reply e-mail.
8. A success message is displayed. Click **Finish**.

[Back to Index](#)

Scenario 13: Edition Upgrade, Hardware Key Protection

The process below allows you to perform an Edition Upgrade (LV Basic to LV Pro, LV Basic to LV Gold, or LV Pro to LV Gold) to an existing LABELVIEW product (Hardware Key protection).

A) Run the Key Upgrade Utility:

1. To access the Key Upgrade utility, go to **Start > Programs > Teklynx > Upgrade Manager > Key - Upgrade**.
The Key Upgrade wizard will appear.
2. Proceed with the Key Upgrade process by following the on-screen instructions provided in the wizard.

Note: If you get a message that the key could not be found, check that your key is correctly connected to the parallel or USB port. If your connection is fine, check to make sure your HASP drivers are upgraded before upgrading your key. A HASP upgrade wizard is available at www.teklynx.com/HASP.

[Back to Index](#)